

CLAIMS

What is claimed is:

- 5 1. A low-noise buffer for a digital logic signal, comprising:
an analog amplifier having a unity-gain bandwidth
substantially greater than a maximum switching rate of the digital
logic signal;
a converter circuit operative to convert the digital logic
10 signal to a ramp signal provided as an input to the analog
amplifier, the ramp signal having a slope determined by a bias
current and an input capacitance of the analog amplifier; and
a bias circuit operative to generate the bias current in a
manner ensuring that the bias current varies as the input
15 capacitance of the analog amplifier varies due to variations in
the manufacturing process of the buffer, such that the slope of
the ramp signal remains substantially constant despite the
variations in the manufacturing process of the buffer.
- 20 2. A low-noise buffer according to claim 1, wherein the analog
amplifier comprises:
an input stage including a differential pair of PMOS
transistors in cascode configuration; and
a differential-to-single-ended, push-pull output stage.
- 25 3. A low-noise buffer according to claim 1, wherein the ramp
circuit comprises a switched current source, the magnitude of the
current supplied by the switched current source being established
by the bias current.
- 30 4. A low-noise buffer according to claim 3, wherein the ramp
circuit comprises:

a first switched current mirror operative to generate current of one polarity when the digital logic signal has a first logic value; and

5 a second switched current mirror operative to generate current of the opposite polarity when the digital logic signal has a second logic value.

10 5. A low-noise buffer according to claim 1, wherein the bias circuit comprises a switched-capacitor resistor across which a predetermined reference voltage is placed to generate the bias current, the switched-capacitor resistor including a capacitor having capacitance that varies as the input capacitance of the analog amplifier varies due to variations in the manufacturing process of the buffer.